

AD630861

NO# 5307:7

ORC 65-33  
DECEMBER 1965

AN EXTENSION OF GENERALIZED  
UPPER BOUNDED TECHNIQUES I  
FOR STRUCTURED LINEAR PROGRAMS

by  
M. Sakarovitch  
and  
R. Saigal

CLEARINGHOUSE FOR FEDERAL SCIENTIFIC AND TECHNICAL INFORMATION			
Hardcopy	Microfiche		
\$1.60	\$0.50	17 pp	as
ARCHIVE COPY			

Code 1

OPERATIONS RESEARCH CENTER

COLLEGE OF ENGINEERING

UNIVERSITY OF CALIFORNIA-BERKELEY



AN EXTENSION OF GENERALIZED UPPER BOUNDED TECHNIQUES I  
FOR STRUCTURED LINEAR PROGRAMS

by

M. Sakarovitch and R. Saigal  
Operations Research Center  
University of California, Berkeley

December 1965

ORC 65-33

This research has been supported by the Army Research Office under Contract DA-31-124-ARO-D-331, and the National Institutes of Health under Grant GM-9606 and the National Science Foundation under Grant GP-4593 with the University of California. Reproduction in whole or in part is permitted for any purpose of the United States Government.

## ABSTRACT

An algorithm is developed for solving a special structured linear program. The particular structure studied has a large number of blocks coupled together by a relatively few connecting equations. The method proposed is an extension of [2] and, from the basis, defines a working basis which is much smaller in size than the original. Two methods of updating the working basis are proposed.

## INTRODUCTION

In this paper we propose a device for solving a large scale linear programming problem of a special configuration. The method proposed is an extension of "Generalized Upper Bounded Techniques - I" [2] to a larger class of problems.

The special configuration is the following:

$$\textcircled{1} \quad \left\{ \begin{array}{lcl} \boxed{A'_0 x_0 + A'_1 x_1 + \dots + A'_L x_L} & = & b_0 \\ \boxed{A_1 x_1} & = & b_1 \\ & & \boxed{A_L x_L} = b_L \\ \gamma_0 x_0 + \gamma_1 x_1 + \dots + \gamma_L x_L & = & z(\min) \end{array} \right.$$

$x$  is a vector of  $N$  components which can be written  $x = (x_0, x_1, \dots, x_L)$

where  $x_i$  has  $n_i$  components and  $N = n_0 + n_1 + \dots + n_L$ .

$A'_i$  is an  $m_0 \times n_i$  matrix;

$A_i$  is an  $m_i \times n_i$  matrix.

$M = m_0 + m_1 + \dots + m_L$  is the number of equations of the system which we will assume to be nonredundant and which can be written for short:

$$\textcircled{1'} \quad \begin{cases} \underline{A}x = \underline{b} \\ \gamma x = z(\min) \end{cases} \quad \text{where } \underline{A} \text{ is an } M \times N \text{ matrix}.$$

The basic assumption is that  $L \gg m_0$ .

Although we can save an important computational work with respect to the simplex method by applying the decomposition principle [1] to Problem (1') we will, rather, taking advantage of the very special condition  $L \gg m_0$ , extend the device given

by Dantzig and Van Slyke in [2]: From the basis of the system a 'working basis' is derived which is considerably smaller in size. Computations are done, as much as possible, on this working basis which result in a substantial savings in computation and storage. A way is given to find the next working basis from iteration to iteration.

In a first part we give definitions and theorems; in a second part we give the general method; and in a third part we give two different ways of updating.

1. SOME DEFINITIONS AND THEOREMS -  $S_i$  will refer (depending on context) either to the set of components of  $x_i$  or to the set of corresponding columns of the matrix  $A$ .

Suppose we are at some stage of the process and that  $\underline{B}$  is a basis for the system. Let

$$\begin{bmatrix} B_i \\ 0 \\ B_i \\ 0 \end{bmatrix}$$

be the contribution of the set  $S_i$  to the basis  $\underline{B}$ .

THEOREM 1: At least  $m_i$  variables from each set  $S_i$  ( $i = 1, \dots, L$ ) are basic.

Proof: Suppose  $S_p$  has less than  $m_p$  basic columns. Then there exists a linear combination of rows of  $B_p$  which vanishes: (i)  $\lambda_p B_p = 0$ . Now we can define  $\lambda = (0, \dots, 0, \lambda_p, 0, \dots, 0)$  such that  $\lambda \underline{B} = \lambda_p B_p = 0$ , which contradicts the fact that  $\underline{B}$  is nonsingular.

Remark: It follows from (i) that if  $B_p$  has exactly  $m_p$  basic columns, it is nonsingular.

THEOREM 2: The number of sets  $S_i$  containing more than  $m_i$  basic variables is at most  $m_0$ .

Proof: By the assumption of full rank, each basis has exactly  $M$  vectors. By Theorem 1, each set  $S_i$  contains at least  $m_i$  basic variables; this leaves  $m_0$  to make up sets of more than  $m_i$  basic variables.

Definition: A set  $S_i$  will be said to be essential if it has more than  $m_i$  basic variables; the set  $S_0$  is always put in the essential class. The other sets will be called inessential.

$$\xi = \{i | S_i \text{ is essential}\}$$

$$\bar{\xi} = \{i | S_i \text{ is inessential}\}.$$

II. THE GENERAL METHOD - The reduced system is defined by deleting the subsystems  $A_i x_i = b_i$  where  $S_i$  is inessential. The set of essential basic columns restricted to the reduced system is our working basis  $B$ .

The value of inessential basic variables is determined from:

$$(1) \quad B_i x_i' = b_i$$

where  $B_i$  is square and nonsingular. These smaller systems are readily solved.

THEOREM 3: The working basis is a basis for the reduced system.

Proof: The number of equations in the reduced system equals the number of variables in the working basis since for each inessential set we remove exactly  $m_i$  equations and  $m_i$  basic columns from the square basis  $\underline{B}$ . The columns of the working basis are linearly independent since they differ from the columns of the basis  $\underline{B}$  by a bunch of zeros in the inessential part, and the columns of  $\underline{B}$  are linearly independent.

The size of the working basis  $B$  is  $m_0 + \sum_{i \in \xi} m_i$ , considerably smaller than that of  $\underline{B}$ . Note that the size of  $B$  changes from step to step, and that even the number of blocks in  $B$  (which is bounded by  $m_0$ ) changes from step to step.

Suppose we have a basis  $\underline{B}$ , the columns of which will be denoted  $\underline{B}^j$  ( $j=1, \dots$ ).  
 Let  $B = [B^i, i = 1, \dots, |B|]$  be the corresponding working basis.

The problem is:

- a) To determine which column enters the basis;
- b) To determine which column is dropped from the basis.

1) Let

$\underline{\pi} = (\pi_0, \pi_1, \dots, \pi_L)$  be the price vector corresponding to  $\underline{B}$ ;

$\pi = (\pi_0, \pi_1 \mid i \in \xi)$  be the price vector corresponding to  $B$ ;

$\gamma = (\gamma_0, \gamma_1, \dots, \gamma_L)$  be the cost vector;

$\underline{c} = (c_0, c_1, \dots, c_L)$  be the cost vector associated with  $\underline{B}$ ;

$c = (c_i \mid i \in \xi)$  be the cost vector associated with  $B$ .

The equation

$$(2) \quad \underline{\pi} \underline{B} = \underline{c}$$

defines the price vector. The point is that this equation can be written

$$(2') \quad \pi B = c \quad ;$$

$$(2'') \quad \pi_0 B_0^! + \pi_i B_i = c_i \quad i \in \bar{\xi} \quad .$$

We will later give different ways of solving (2'); (2') being solved, substituting  $\pi_0$  in (2'') gives  $\pi_i$  in an easy way.

Let  $A_\sigma^s$  and  $A_\sigma'^s$  denote the  $s^{\text{th}}$  column of matrices  $A_\sigma$  and  $A_\sigma'$  respectively.

$$\underline{A}_\sigma^s = \begin{pmatrix} A_\sigma'^s \\ 0 \\ A_\sigma^s \\ 0 \end{pmatrix} \quad \text{is the corresponding column of } \underline{A} \quad .$$

M). The column to enter the basis will be given by the usual criterion:

$$\bar{y}_\sigma^s = y_\sigma^s - \pi \frac{A_\sigma^s}{A_\tau^j} = \min_{\substack{0 \leq \tau \leq L \\ 1 \leq j \leq n_\tau}} (y_\tau^j - \pi \frac{A_\tau^j}{A_\tau^j})$$

If  $\bar{y}_\sigma^s \geq 0$ , we have found an optimal basic solution; if not, we bring  $\frac{A_\sigma^s}{A_\tau^j}$  into the basis.

2)  $\frac{A_\sigma^s}{A_\tau^j} \in S_\sigma$ . If  $S_\sigma$  is essential we have not to worry about the inessential part of the problem which remains unchanged. We simply pivot in the reduced system with the usual criterion for picking the column to drop. We then have to update the right-hand side, and the entering column is the reduced system. That is, to solve

$$(3) \quad B \tilde{A}_\sigma^s = A_\sigma^s ;$$

$$(4) \quad B \tilde{b} = b .$$

We postpone to a later part the discussion of how (3) and (4) are actually solved. Note that in this case, since  $B$  is assumed to be of a reasonable size, the updating is simple.

If  $S_\sigma$  is not essential we have to solve, instead of (3) and (4), the more complicated systems:

$$(3') \quad \underline{B} \underline{\tilde{A}}_\sigma^s = \underline{A}_\sigma^s ;$$

$$(4') \quad \underline{B} \underline{\tilde{b}} = \underline{b} .$$

We will now prove that solving (3') and (4') is, in fact, equivalent to solving (3) and (4).

Let  $\tilde{A}_\sigma^s$ ,  $\tilde{b}$  denote the part of the updated columns which correspond to the working basis.



B	$B'_k$	$B'_\sigma$	$B'_L$
	$B_k$		
		$B_\sigma$	
			$B_L$

$$\begin{bmatrix} \tilde{A}'^s_\sigma \\ \tilde{d}_k \\ \vdots \\ \tilde{A}^s_\sigma \\ \vdots \\ \tilde{d}_L \end{bmatrix}, \begin{bmatrix} \tilde{b} \\ \tilde{b}_k \\ \vdots \\ \tilde{b}_\sigma \\ \vdots \\ \tilde{b}_L \end{bmatrix} = \begin{bmatrix} A'^s_\sigma \\ 0 \\ \vdots \\ A^s_\sigma \\ \vdots \\ 0 \end{bmatrix}, \begin{bmatrix} b \\ b_k \\ \vdots \\ b_\sigma \\ \vdots \\ b_L \end{bmatrix}$$

This can be written:

$$(5) \quad \left\{ \begin{array}{l} B_k \\ \vdots \\ B_\sigma \\ \vdots \\ B_L \end{array} \right. \quad \begin{array}{l} \tilde{d}_k = 0 \\ \vdots \\ \tilde{A}^s_\sigma = A^s_\sigma \\ \vdots \\ \tilde{d}_L = 0 \end{array}$$

$$(6) \quad \left\{ \begin{array}{l} B_k \\ \vdots \\ B_\sigma \\ \vdots \\ B_L \end{array} \right. \quad \begin{array}{l} \tilde{b}_k = b_k \\ \vdots \\ \tilde{b}_\sigma = b_\sigma \\ \vdots \\ \tilde{b}_L = b_L \end{array}$$

$$(3'') \quad B\tilde{A}'^s_\sigma = \begin{bmatrix} A'^s_\sigma \\ 0 \end{bmatrix} - \begin{bmatrix} B'_\sigma \\ 0 \end{bmatrix} \tilde{A}^s_\sigma ; \quad (4'') \quad B\tilde{b} = b - \sum_{i \in \bar{S}} \begin{bmatrix} B'_i \\ 0 \end{bmatrix} \tilde{b}_i$$

And we see that if we suppose the systems in (5) and (6) are of very low order and that their solution is readily at hand, we have only to solve (3'') and (4''), which are exactly of the same type as (3) and (4).

By the usual simplex criterion we now know which column is to be dropped. Let us suppose that the column to be dropped belongs to the set  $S_\tau$ . Two cases can occur:

a)  $S_\tau$  is inessential, so  $S_\tau$  can only be  $S_\sigma$ . Then the pivoting is only done in the inessential sub-basis  $B_\sigma$ , and the working basis does not change.

b)  $S_\tau$  is essential, so the method of pivoting is as follows:

Step I - Introduce  $S_\sigma$  in the essential set (the size of the working basis is increased by  $m_\sigma$ ).

Step II - Pivot in the new reduced system.

Step III - If the number of variables in  $S_\tau$  is now  $m_\tau$ ,<sup>†</sup> make  $S_\tau$  inessential (the size of the working basis is decreased by  $m_\tau$ ).

The algebraic work involved in Equations (2'), (3) and (4) (or (3'') and (4'')) can be done in essentially two ways. The first is the Revised Simplex Method; the justification of using it is that the working basis will remain of a reasonable size. The second is to solve the system, instead of inverting the matrix  $B$ , by a triangularization process which is inspired of [3].

### III. UPDATING PROCESS -

A. Revised Simplex Method: Suppose we have an inverse of the working basis  $B^{-1}$ ; we want to find  $B^{*-1}$  where  $B^*$  is the basis for the next iteration. If  $S_\sigma$  is essential, we pivot in the reduced system and simply apply the revised simplex algorithm in the reduced system. If  $S_\sigma$  and  $S_\tau$  are inessential, the working basis does not change. If  $S_\sigma$  is inessential and  $S_\tau$  is essential, we will describe the three steps outlined above.

---

<sup>†</sup> If the essential set  $S_\tau$  had more than  $m_{\tau+1}$  basic columns beforehand, this will not be the case.

Step 1. Define

$$\tilde{B} = \begin{array}{|c|c|} \hline B & B'_{\sigma} \\ \hline 0 & B_{\sigma} \\ \hline \end{array} \quad Q = \begin{array}{|c|} \hline B'_{\sigma} \\ \hline \end{array} ;$$

then it is easy to see that:

$$\tilde{B}^{-1} = \begin{array}{|c|c|} \hline B^{-1} & Q' \\ \hline 0 & B_{\sigma}^{-1} \\ \hline \end{array} \quad \text{with } Q' = B^{-1}QB_{\sigma}^{-1} .$$

Step 2. Now we are as in the first case and we use the modified simplex method to get  $\tilde{B}^{*-1}$  (where  $\tilde{B}^*$  is obtained from  $\tilde{B}$  by pivoting in the reduced system).

Step 3. If  $B_{\tau}$  is now square, we can rearrange the equations and variables in  $\tilde{B}^*$  so that it looks like this:

$$\tilde{B}^* = \begin{array}{|c|c|} \hline B^* & B'_{\tau} \\ \hline & B_{\tau} \\ \hline \end{array} \quad \tilde{B}^{*-1} = \begin{array}{|c|c|} \hline B^{*-1} & Q'_{\tau} \\ \hline & B_{\tau}^{-1} \\ \hline \end{array} .$$

$B^*$  and  $B^{*-1}$  are now obtained by dropping the column and rows corresponding to  $B_{\tau}$ .

B. Compact Basis Triangularization: Any equations of the type  $Bx = b$  or  $\pi B = c$  where  $B$  is an  $m \times m$  nonsingular matrix can be solved by triangularizing  $B$  (see [3]). It has been pointed out in [3] that triangularizing may be an efficient method in cases where  $B$  has a special structure (such as block angular).

Triangularizing is equivalent to pre-multiplying  $B$  by a set of elementary matrices  $E_i$

$$T = E_1, E_2, \dots, E_m B$$

where, in the notation of [3],

$T$  is the triangularized form of  $B$  ;

$E_1, \dots, E_m$  is the compact  $E$ -structure.

To solve  $\pi B = c$  (Equations (2') and (2'') ), we solve

$$\pi^* T = c$$

and

$$\pi = E_1, E_2, \dots, E_m \pi^*$$

To solve  $Bx = b$  (Equations (3),(4),(5),(6) ), we find

$$b^* = E_1, E_2, \dots, E_m b$$

and solve

$$Tx = b^*$$

Having determined  $S_\sigma$  and  $S_\tau$ , we now show the steps in pivoting.

If  $S_\sigma$  is essential, we pivot in the reduced working basis. If  $S_\sigma$  and  $S_\tau$  are inessential, we pivot in the smaller basis  $B_\sigma$ . If  $S_\sigma$  is inessential and  $S_\tau$  essential, then we show the three steps.

Let  $T_\sigma$  be the triangularized form of  $B_\sigma$ ,  $E_\sigma$  its compact  $E$ -structure, and  $J$  the permutation matrix used to triangularize  $B$ . Let  $T$  be the

triangularized form of  $B$ , and  $E$  its compact  $E$ -structure.

Step 1. Introducing  $S_\sigma$  into the essential class, we modify the working basis by introducing  $B_\sigma$  into it. We get<sup>†</sup>

$$\begin{aligned} \text{New } T &= \begin{array}{|c|c|} \hline T_\sigma & 0 \\ \hline EJQ & T \\ \hline \end{array} & Q = \begin{array}{|c|} \hline B'_\sigma \\ \hline 0 \\ \hline \end{array} \\ \\ \text{New } E &= \begin{array}{|c|c|} \hline E_\sigma & 0 \\ \hline 0 & E \\ \hline \end{array} \end{aligned}$$

Step 2. Apply the pivot operation in the new  $B$ .

Step 3. Assume  $\xi_\tau$  has become inessential; to remove this block from the working basis, assume the columns of  $S_\tau$  in  $B$  lie between  $i^{\text{th}}$  and  $i+m_\tau^{\text{th}}$  column. Define

$$\begin{aligned} T &= \begin{array}{c} \begin{array}{|c|c|c|} \hline & i & i+m_\tau \\ \hline T_1 & & 0 \\ \hline & T_2 & \\ \hline T_4 & & T_3 \\ \hline \end{array} \end{array} & E = \begin{array}{c} \begin{array}{|c|c|c|} \hline & i & i+m_\tau \\ \hline E_1 & & E_4 \\ \hline & E_2 & \\ \hline & & E_3 \\ \hline \end{array} \end{array} \end{aligned}$$

Then

---

<sup>†</sup> Note: If we introduce the inessential set  $S_\sigma$  at the top LHS of the  $T$  and  $E$ , we always obtain the new  $E$  structure in this manner.

triangularized form of  $B$ , and  $E$  its compact  $E$ -structure.

Step 1. Introducing  $S_\sigma$  into the essential class, we modify the working basis by introducing  $B_\sigma$  into it. We get<sup>†</sup>

$$\begin{aligned} \text{New } T &= \begin{array}{|c|c|} \hline T_\sigma & 0 \\ \hline E_{JQ} & T \\ \hline \end{array} & Q = \begin{array}{|c|} \hline B'_\sigma \\ \hline 0 \\ \hline \end{array} \\ \\ \text{New } E &= \begin{array}{|c|c|} \hline E_\sigma & 0 \\ \hline 0 & E \\ \hline \end{array} \end{aligned}$$

Step 2. Apply the pivot operation in the new  $B$ .

Step 3. Assume  $\xi_\tau$  has become inessential; to remove this block from the working basis, assume the columns of  $S_\tau$  in  $B$  lie between  $i^{\text{th}}$  and  $i+m_\tau^{\text{th}}$  column. Define

$$\begin{aligned} T &= \begin{array}{|c|c|c|} \hline & i & i+m_\tau \\ \hline T_1 & & 0 \\ \hline & T_2 & \\ \hline T_4 & & T_3 \\ \hline \end{array} & E = \begin{array}{|c|c|c|} \hline & i & i+m_\tau \\ \hline E_1 & & E_4 \\ \hline & E_2 & \\ \hline & & E_3 \\ \hline \end{array} \end{aligned}$$

Then

---

<sup>†</sup> Note: If we introduce the inessential set  $S_\sigma$  at the top LHS of the  $T$  and  $E$ , we always obtain the new  $E$  structure in this manner.

new T =

$T_1$	0
$T_4$	$T_3$

new E =

$E_1$	$E_4$
	$E_3$

and

$$T_\tau = T_2$$

$$E_\tau = E_2$$

.

In conclusion, it seems that Method A may be preferred if the working basis is of small size and if the process of the revised simplex algorithm on it is not too long, as Method B will be preferred if the working basis itself is of large dimension.

## REFERENCES

- [1] Dantzig, G. B., Linear Programming and Extensions, Princeton University Press, Princeton, New Jersey, Chapter 23 (1963).
- [2] Dantzig, G. B., and R. M. Van Slyke, Generalized Upper Bounding Techniques for Linear Programming - I," Operations Research Center 64-17, University of California, Berkeley (March 1965).
- [3] Dantzig, G. B., "Compact Basis Triangularization for the Simplex Method," Recent Advances in Mathematical Programming, P. Wolfe and R. L. Graves, Eds., pp. 125-132, McGraw-Hill (1963).
- [4] Bennett, John, "An Approach to Some Structured Linear Programming Problems," Basser Computing Department, School of Physics, University of Sydney, Australia (March 1963).



Unclassified

Security Classification

DOCUMENT CONTROL DATA - R&D		
(Security classification of title, body of abstract and indexing annotation must be entered when the overall report is classified)		
1. ORIGINATING ACTIVITY (Corporate author)		2a. REPORT SECURITY CLASSIFICATION
University of California (Berkeley)		Unclassified
		2b. GROUP
		NA
3. REPORT TITLE		
An Extension of Generalized Upper Bounded Techniques I for Structured Linear Programs		
4. DESCRIPTIVE NOTES (Type of report and inclusive dates)		
Technical Report - December 1965		
5. AUTHOR(S) (Last name, first name, initial)		
Sakarovitch, M. Saigal, R.		
6. REPORT DATE	7a. TOTAL NO. OF PAGES	7b. NO. OF REFS
December 1965	12	4
8a. CONTRACT OR GRANT NO.	9a. ORIGINATOR'S REPORT NUMBER(S)	
DA-31-124-ARO-D-331	ORC 65-33	
b. PROJECT NO.	9b. OTHER REPORT NO(S) (Any other numbers that may be assigned this report)	
20014501B14C	5307.7	
c.		
d.		
10. AVAILABILITY/LIMITATION NOTICES		
Qualified requesters may obtain copies of this report from DDC.		
11. SUPPLEMENTARY NOTES		12. SPONSORING MILITARY ACTIVITY
None		U. S. Army Research Office-Durham Box CM, Duke Station Durham, N. C. 27706
13. ABSTRACT		
<p>An algorithm is developed for solving a special structured linear program. The particular structure studied has a large number of blocks coupled together by a relatively few connecting equations. The method proposed is an extension of "Generalized Upper Bounding Techniques for Linear Programming-I," by G. B. Dantzig and R. M. Van Slyke (March 1965) and, from the basis, defines a working basis which is much smaller in size than the original. Two methods of updating the working basis are proposed.</p>		

14. KEY WORDS	LINK A		LINK B		LINK C	
	ROLE	WT	ROLE	WT	ROLE	WT
Structured Linear Programs Algorithms						

INSTRUCTIONS

1. **ORIGINATING ACTIVITY:** Enter the name and address of the contractor, subcontractor, grantee, Department of Defense activity or other organization (*corporate author*) issuing the report.

2a. **REPORT SECURITY CLASSIFICATION:** Enter the overall security classification of the report. Indicate whether "Restricted Data" is included. Marking is to be in accordance with appropriate security regulations.

2b. **GROUP:** Automatic downgrading is specified in DoD Directive 5200.10 and Armed Forces Industrial Manual. Enter the group number. Also, when applicable, show that optional markings have been used for Group 3 and Group 4 as authorized.

3. **REPORT TITLE:** Enter the complete report title in all capital letters. Titles in all cases should be unclassified. If a meaningful title cannot be selected without classification, show title classification in all capitals in parenthesis immediately following the title.

4. **DESCRIPTIVE NOTES:** If appropriate, enter the type of report, e.g., interim, progress, summary, annual, or final. Give the inclusive dates when a specific reporting period is covered.

5. **AUTHOR(S):** Enter the name(s) of author(s) as shown on or in the report. Enter last name, first name, middle initial. If military, show rank and branch of service. The name of the principal author is an absolute minimum requirement.

6. **REPORT DATE:** Enter the date of the report as day, month, year; or month, year. If more than one date appears on the report, use date of publication.

7a. **TOTAL NUMBER OF PAGES:** The total page count should follow normal pagination procedures, i.e., enter the number of pages containing information.

7b. **NUMBER OF REFERENCES:** Enter the total number of references cited in the report.

8a. **CONTRACT OR GRANT NUMBER:** If appropriate, enter the applicable number of the contract or grant under which the report was written.

8b, 8c, & 8d. **PROJECT NUMBER:** Enter the appropriate military department identification, such as project number, subproject number, system numbers, task number, etc.

9a. **ORIGINATOR'S REPORT NUMBER(S):** Enter the official report number by which the document will be identified and controlled by the originating activity. This number must be unique to this report.

9b. **OTHER REPORT NUMBER(S):** If the report has been assigned any other report numbers (*either by the originator or by the sponsor*), also enter this number(s).

10. **AVAILABILITY/LIMITATION NOTICES:** Enter any limitations on further dissemination of the report, other than those imposed by security classification, using standard statements such as:

- (1) "Qualified requesters may obtain copies of this report from DDC."
- (2) "Foreign announcement and dissemination of this report by DDC is not authorized."
- (3) "U. S. Government agencies may obtain copies of this report directly from DDC. Other qualified DDC users shall request through \_\_\_\_\_."
- (4) "U. S. military agencies may obtain copies of this report directly from DDC. Other qualified users shall request through \_\_\_\_\_."
- (5) "All distribution of this report is controlled. Qualified DDC users shall request through \_\_\_\_\_."

If the report has been furnished to the Office of Technical Services, Department of Commerce, for sale to the public, indicate this fact and enter the price, if known.

11. **SUPPLEMENTARY NOTES:** Use for additional explanatory notes.

12. **SPONSORING MILITARY ACTIVITY:** Enter the name of the departmental project office or laboratory sponsoring (*paying for*) the research and development. Include address.

13. **ABSTRACT:** Enter an abstract giving a brief and factual summary of the document indicative of the report, even though it may also appear elsewhere in the body of the technical report. If additional space is required, a continuation sheet shall be attached.

It is highly desirable that the abstract of classified reports be unclassified. Each paragraph of the abstract shall end with an indication of the military security classification of the information in the paragraph, represented as (TS), (S), (C), or (U).

There is no limitation on the length of the abstract. However, the suggested length is from 150 to 225 words.

14. **KEY WORDS:** Key words are technically meaningful terms or short phrases that characterize a report and may be used as index entries for cataloging the report. Key words must be selected so that no security classification is required. Identifiers, such as equipment model designation, trade name, military project code name, geographic location, may be used as key words but will be followed by an indication of technical context. The assignment of links, rules, and weights is optional.